

	7200MA MODBUS Application Notes	
--	---------------------------------	--

(7) Inverter return messages

- ① Please refer to the “ Message Format” in next page about inverter returning messages for more detail descriptions.
- ② It needs 5ms to return messages after inverter had received normal message from host controller.
- ③ In next two cases, inverter does not return any message :
 - There are any error detection in received data message (parity error, framing error, overrun error or CRC-16 error).
 - Slave Address character is different to parameter Sn-36 (Inverter Slave No.).

A	C	D												7/29
---	---	---	--	--	--	--	--	--	--	--	--	--	--	------

